


VERIFICATION

The undersigned, of the below address, hereby certifies that he/she well knows both the English and Japanese languages, and that the attached is an accurate English translation of the Japanese Patent application filed on October 8, 2002 under No. P2002-295429.

The undersigned declares further that all statements made herein of his/her own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issuing thereon.

Signed this 17th day of June, 2009.

Signature:

A handwritten signature in black ink, appearing to be 'Shiro TERASAKI', written over a horizontal line.

Name: Shiro TERASAKI

Address: c/o Soei Patent & Law Firm Ginza First Bldg.,
10-6, Ginza 1-chome, Chuo-ku, Tokyo 104-0061
Japan

JAPAN PATENT OFFICE

This is to certify that the annexed is a true copy of the following application as filed with this Office.

Date of Application: October 8, 2002

Application Number: Japanese Patent Application
No. 2002-295429

Applicant(s): NTT DoCoMo, Inc.

Commissioner,
Patent Office

(Seal)

(Document Name) Patent Application
(Reference Number) 14-0422
(Presentation Date) October 8, 2002
(Directly) Commissioner of the Patent Office
(IPC) H04N 1/00
(Inventor)

(Residence or Address)

c/o NTT DoCoMo, Inc., 11-1, Nagatacho 2-chome, Chiyoda-ku,
Tokyo

(Name) Satoru ADACHI

(Inventor)

(Residence or Address)

c/o NTT DoCoMo, Inc., 11-1, Nagatacho 2-chome, Chiyoda-ku,
Tokyo

(Name) Minoru ETOH

(Inventor)

(Residence or Address)

c/o NTT DoCoMo, Inc., 11-1, Nagatacho 2-chome, Chiyoda-ku,
Tokyo

(Name) Sadaatsu KATO

(Inventor)

(Residence or Address)

c/o NTT DoCoMo, Inc., 11-1, Nagatacho 2-chome, Chiyoda-ku,
Tokyo

(Name) Thiow Keng TAN

(Applicant)

(Identification Number) 392026693

(Name) NTT DoCoMo, Inc.

(Attorney)

(Identification Number) 100088155

(Patent Attorney)

(Name) Yoshiki HASEGAWA

(Attorney)

(Identification Number) 100092657

(Patent Attorney)

(Name) Shiro TERASAKI

(Attorney)

(Identification Number) 100114270

(Patent Attorney)

(Name) Tomoya KUROKAWA

(Attorney)

(Identification Number) 100108213

(Patent Attorney)

(Name) Toyotaka ABE

(Attorney)

(Identification Number) 100113549

(Patent Attorney)

(Name) Mamoru SUZUKI

(Official Fee)

(Pre-Paid Master Note Number) 014708

(Amount to be paid) 21,000 yen

(Lists of the Article to be presented)

(Name of Article) Specification 1

(Name of Article) Drawing 1

(Name of Article) Abstract 1

(Proof Reading) Required

[Document Name] Specification

[Title of the Invention] IMAGE ENCODING METHOD, IMAGE
DECODING METHOD, IMAGE ENCODING APPARATUS, IMAGE
DECODING APPARATUS, IMAGE PROCESSING SYSTEM,
5 IMAGE ENCODING PROGRAM, AND IMAGE DECODING
PROGRAM

[Claims]

[Claim 1] An image encoding method of dividing image
signals into blocks, performing an orthogonal transform of each block,
10 reading resultant orthogonal transform coefficients to obtain a
coefficient string, and performing entropy coding thereof, the image
encoding method comprising:

a block selecting step of selecting a size of a block for the
orthogonal transform, out of a plurality of blocks of different sizes;

15 a coefficient string dividing step of, when a block of a size
larger than a minimum size is selected in the block selecting step,
dividing a coefficient string in said block into a plurality of coefficient
strings of a length equal to that of a coefficient string in a block of the
minimum size; and

20 an encoding step of performing entropy coding adapted to the
coefficient string in the block of the minimum size.

[Claim 2] The image encoding method according to Claim 1,
wherein the coefficient string dividing step is configured to read
coefficients of the coefficient string from the lowest in a low frequency
25 region and assign the read coefficients one by one in order to the
plurality of coefficient strings of the length equal to that of the

coefficient string in the block of the minimum size, thereby obtaining the divided coefficient strings.

[Claim 3] The image encoding method according to Claim 1, wherein the coefficient string dividing step is configured to read
5 coefficients of the coefficient string from the lowest in a low frequency region and repeatedly perform reading of coefficients by the number equal to the number of coefficients in the coefficient string in the block of the minimum size to obtain a divided coefficient string, thereby obtaining the divided coefficient strings.

[Claim 4] An image decoding method of decoding encoded
10 data encoded by an image encoding method of dividing image signals into blocks, performing an orthogonal transform of each block, reading resultant orthogonal transform coefficients to obtain a coefficient string, and performing entropy coding thereof, the image decoding method comprising:
15

a block selecting step of selecting a size of a block for the orthogonal transform, out of a plurality of blocks of different sizes;

a decoding step for performing decoding of the encoded data by entropy coding adapted to a coefficient string in a block of a minimum
20 size out of the plurality of blocks; and

a coefficient string constructing step of, when a block of a size larger than the minimum size is selected in the block selecting step, constructing a coefficient string of the block of the larger size from a plurality of coefficient strings decoded in the decoding step.

[Claim 5] The image decoding method according to Claim 4,
25 wherein the coefficient string constructing step is configured to read

coefficients in the plurality of coefficient strings decoded in the decoding step, from the lowest in a low frequency region and write the coefficients read out of the respective coefficient strings, one by one in order into a new coefficient string from the low frequency region, thereby obtaining the constructed coefficient string.

[Claim 6] The image decoding method according to Claim 4, wherein the coefficient string constructing step is configured to read coefficients in the plurality of coefficient strings decoded in the decoding step, from the lowest in a low frequency region and write the read coefficients in units of the original coefficient strings into a new coefficient string from the low frequency region, thereby obtaining the constructed coefficient string.

[Claim 7] An image encoding apparatus of dividing image signals into blocks, performing an orthogonal transform of each block, reading resultant orthogonal transform coefficients to obtain a coefficient string, and performing entropy coding thereof, the image encoding apparatus comprising:

block selecting means for selecting a size of a block for the orthogonal transform, out of a plurality of blocks of different sizes;

coefficient string dividing means for, when a block of a size larger than a minimum size is selected by the block selecting means, dividing a coefficient string in said block into a plurality of coefficient strings of a length equal to that of a coefficient string in a block of the minimum size; and

encoding means for performing entropy coding adapted to the coefficient string in the block of the minimum size.

[Claim 8] The image encoding apparatus according to Claim 7, wherein the coefficient string dividing means is configured to read coefficients of the coefficient string from the lowest in a low frequency region and assign the read coefficients one by one in order to the plurality of coefficient strings of the length equal to that of the coefficient string in the block of the minimum size, thereby obtaining the divided coefficient strings.

[Claim 9] The image encoding apparatus according to Claim 7, wherein the coefficient string dividing means is configured to read coefficients of the coefficient string from the lowest in a low frequency region and repeatedly perform reading of coefficients by the number equal to the number of coefficients in the coefficient string in the block of the minimum size to obtain a divided coefficient string, thereby obtaining the divided coefficient strings.

[Claim 10] An image decoding apparatus of decoding encoded data encoded by an image encoding method of dividing image signals into blocks, performing an orthogonal transform of each block, reading resultant orthogonal transform coefficients to obtain a coefficient string, and performing entropy coding thereof, the image decoding apparatus comprising:

block selecting means for selecting a size of a block for the orthogonal transform, out of a plurality of blocks of different sizes;

decoding means for performing decoding of the encoded data by entropy coding adapted to a coefficient string in a block of a minimum size out of the plurality of blocks; and

coefficient string constructing means for, when a block of a size

larger than the minimum size is selected by the block selecting means, constructing a coefficient string of the block of the larger size from a plurality of coefficient strings decoded by the decoding means.

[Claim 11] The image decoding apparatus according to Claim 10, wherein the coefficient string constructing means is configured to read coefficients in the plurality of coefficient strings decoded by the decoding means, from the lowest in a low frequency region and write the coefficients read out of the respective coefficient strings, one by one in order into a new coefficient string from the low frequency region, thereby obtaining the constructed coefficient string.

[Claim 12] The image decoding apparatus according to Claim 10, wherein the coefficient string constructing means is configured to read coefficients in the plurality of coefficient strings decoded by the decoding means, from the lowest in a low frequency region and write the read coefficients in units of the original coefficient strings into a new coefficient string from the low frequency region, thereby obtaining the constructed coefficient string.

[Claim 13] An image processing system comprising: the image encoding apparatus according to any one of Claims 7 to 9, and the image decoding apparatus according to any one of Claims 10 to 12.

[Claim 14] An image encoding program for dividing image signals into blocks, performing an orthogonal transform of each block, reading resultant orthogonal transform coefficients to obtain a coefficient string, and performing entropy coding thereof, the image encoding program letting a computer execute:

a block selecting step of selecting a size of a block for the

orthogonal transform, out of a plurality of blocks of different sizes;

a coefficient string dividing step of, when a block of a size larger than a minimum size is selected in the block selecting step, dividing a coefficient string in said block into a plurality of coefficient strings of a length equal to that of a coefficient string in a block of the minimum size; and

an encoding step of performing entropy coding adapted to the coefficient string in the block of the minimum size.

[Claim 15] The image encoding program according to Claim 14, wherein the coefficient string dividing step is configured to read coefficients of the coefficient string from the lowest in a low frequency region and assign the read coefficients one by one in order to the plurality of coefficient strings of the length equal to that of the coefficient string in the block of the minimum size, thereby obtaining the divided coefficient strings.

[Claim 16] The image encoding program according to Claim 14, wherein the coefficient string dividing step is configured to read coefficients of the coefficient string from the lowest in a low frequency region and repeatedly perform reading of coefficients by the number equal to the number of coefficients in the coefficient string in the block of the minimum size to obtain a divided coefficient string, thereby obtaining the divided coefficient strings.

[Claim 17] An image decoding program for decoding encoded data encoded by an image encoding method of dividing image signals into blocks, performing an orthogonal transform of each block, reading resultant orthogonal transform coefficients to obtain a

coefficient string, and performing entropy coding thereof, the image decoding program letting a computer execute:

a block selecting step of selecting a size of a block for the orthogonal transform, out of a plurality of blocks of different sizes;

5 a decoding step for performing decoding of the encoded data by entropy coding adapted to a coefficient string in a block of a minimum size out of the plurality of blocks; and

10 a coefficient string constructing step of, when a block of a size larger than the minimum size is selected in the block selecting step, constructing a coefficient string of the block of the larger size from a plurality of coefficient strings decoded in the decoding step.

[Claim 18] The image decoding program according to Claim 17, wherein the coefficient string constructing step is configured to read coefficients in the plurality of coefficient strings decoded in the decoding step, from the lowest in a low frequency region and write the coefficients read out of the respective coefficient strings, one by one in order into a new coefficient string from the low frequency region, thereby obtaining the constructed coefficient string.

20 [Claim 19] The image decoding program according to Claim 17, wherein the coefficient string constructing step is configured to read coefficients in the plurality of coefficient strings decoded in the decoding step, from the lowest in a low frequency region and write the read coefficients in units of the original coefficient strings into a new coefficient string from the low frequency region, thereby obtaining the constructed coefficient string.

25 [Detailed Description of the Invention]

[0001]

[Technical Field to which the Invention Pertains]

The present invention relates to an image encoding method, an image decoding method, an image encoding apparatus, an image decoding apparatus, an image processing system, an image encoding program, and an image decoding program capable of implementing efficient entropy coding of orthogonal transform coefficients in an orthogonal transform permitting selection among multiple block sizes.

[0002]

[Prior Art]

Encoding techniques of image signals are used for transmission and for accumulation and reproduction of image signals of still images, moving images, and so on. Such techniques include known international standard encoding methods, e.g., ISO/IEC International Standard 10918 (hereinafter referred to as JPEG) as an encoding technique for still images, and ISO/IEC international Standard 14496-2 (MPEG-4 Visual, which will be referred to hereinafter as MPEG-4) as an encoding technique for moving images. A newer known encoding method is ITU-T Recommendation H.264; ISO/IEC International Standard 14496-10 (Joint Final Committee Draft of Joint Video Specification, ftp://ftp.imtc-files.org/jvt-experts/2002_07_Klagenfurt/JVT-D157.zip, which will be referred to hereinafter as H.26L), which is a video coding method intended for joint international standardization by ITU-T and ISO/IEC. The general encoding techniques used in these image encoding methods are described, for example, in Non-Patent Document 1.

[0003]

Image signals demonstrate close correlations between spatially neighboring pixels and thus transformation into the frequency domain leads to deviation of information to the low frequency region, which enables reduction of redundancy by making use of the deviation. Therefore, the typical image encoding methods adopt a technique of subjecting image signals to an orthogonal transform to transform them into orthogonal transform coefficients in the frequency domain, so as to achieve deviation of signal components to the low frequency region. Furthermore, the coefficient values are quantized so that small-valued coefficients are converted into zeros. A coefficient string is made by reading the coefficients in order from the lowest in the low frequency region and is subjected to entropy coding taking advantage of the deviation of coefficient values, thus achieving efficient encoding with reduction of redundancy.

[0004]

In this case, the Discrete Cosine Transform (DCT) is commonly used as the orthogonal transform in terms of encoding efficiency and ease of implementation. The orthogonal transform such as the DCT is carried out in units of blocks resulting from division of image signals into blocks each consisting of a plurality of pixels. The size of the blocks, as well as the property of the image signals, largely affects the encoding efficiency.

[0005]

When image signals demonstrate only small change in the spatial property, image signals to be transformed into orthogonal

transform coefficients in a narrow frequency region are widely distributed on an image, and the redundancy can be reduced more with increase in the size of the blocks, i.e., the size of the orthogonal transform, so as to increase the encoding efficiency, as compared with cases using smaller blocks, which raise the need for repeatedly expressing identical orthogonal transform coefficients. When image signals demonstrate large change in the spatial property on the other hand, the increase in the size of blocks results in obtaining various frequency components of orthogonal transform coefficients thereof and thus decreasing the deviation of coefficients, which makes efficient entropy coding difficult and thus decreases the encoding efficiency.

[0006]

In order to take advantage of the change of encoding efficiency due to the changes in the sizes of the blocks for the orthogonal transform and the property of image signals, the technology utilized is one of preparing orthogonal transform means in a plurality of block sizes in advance and adaptively selecting and using a size achieving the best encoding efficiency out of them. This technology is called Adaptive Block size Transforms (ABT) and is adopted in H.26L. Fig. 1 shows orthogonal transform blocks used for the ABT in H.26L. The ABT permits a size achieving the best encoding efficiency to be selected out of four types of orthogonal transform block sizes shown in Figs. 1(b)-(e), for each macroblock of 16×16 pixels shown in Fig. 1(a). Pixel values of each macroblock are equally divided in units of blocks of the selected size and are then subjected to the orthogonal transform. By implementing such selection, it becomes feasible to achieve

efficient reduction of redundancy through the use of the orthogonal transform in accordance with the change in the spatial property of image signals in the macroblocks. Reference should be made to H.26L as to more specific details of the ABT.

5 [0007]

The entropy coding for the orthogonal transform coefficients obtained by the orthogonal transform is effected on a coefficient string obtained by sequentially reading the orthogonal transform coefficients from the lowest in the low frequency region. Fig. 2(a) shows an order of reading coefficients in an orthogonal transform block of 4×4 pixels. Since the coefficients obtained by the orthogonal transform are arranged with the lowest frequency component (i.e., the dc component) at the left upper corner, the coefficients are read out in order from the left upper coefficient to obtain a coefficient string consisting of sixteen coefficients as shown in Fig. 2(b). This reading order is called zig-zag scan.

10

15

[0008]

The coefficients obtained by the orthogonal transform are noncorrelated with each other, and the signal components deviate to the low frequency region. For this reason, when they are further quantized, the lower frequency coefficients are more likely to be nonzero coefficient values, so that many zero-valued coefficients appear in the coefficient string. For example, it produces a sequence of coefficient values as shown in Fig. 2(c). Therefore, for efficient entropy coding of the coefficient string of this distribution, it is common practice in encoding of images to perform the encoding by

20

25

expressing the coefficient string by the numbers of continuous zero coefficients preceding a nonzero coefficient (runs) and coefficient values (levels) of the nonzero coefficients. Such encoding with runs and levels is also used in the entropy coding of orthogonal transform coefficients by the ABT.

[0009]

On the other hand, in order to increase the efficiency more in the entropy coding as described above, H.26L employs the technology called Context-based Adaptive Variable Length Code (CAVLC), which is applied to the orthogonal transform without the use of the ABT, i.e., to cases where the orthogonal transform is always carried out in units of orthogonal transform blocks of 4×4 pixels.

[0010]

The CAVLC in H.26L utilizes the following features: the maximum number of coefficients in the coefficient string obtained from each orthogonal transform block of 4×4 pixels is 16, the magnitude of runs is restricted by this maximum number, and the magnitude of levels tends to be larger at lower frequencies. A number of encoding tables used in variable length encoding are prepared as optimized tables for respective conditions, and they are applied while sequentially being switched, so as to increase the encoding efficiency.

[0011]

For example, in the case where runs are encoded in order, the first run can take a variety of values from 0 to 14 (according to the definition of runs in H.26L, the maximum value of runs is 14, which is two smaller than the total number of coefficients). On the other hand,

a run appearing in the last stage of the sequential encoding of runs can take only one of limited run values, because there is the upper limit to the number of coefficients in the coefficient string. Accordingly, as shown in Fig. 3, the right-side encoding table with the largest number of elements in the encoding table is applied to runs appearing in the initial stage, and the left-side encoding tables with the smaller number of elements in each encoding table are applied to runs appearing in the last stage. This permits assignment of codes of smaller bit counts and thus implements efficient entropy coding. The CAVLC achieves the efficient encoding by making use of the conditions such as the maximum number of coefficients in each block and placing restrictions on the range where values to be encoded can take. Reference should be made to H.26L as to more specific details of the CAVLC.

[0012]

[Non-Patent Document 1] "Basic Technologies on International Image Coding Standards", co-authored by Fumitaka Ono and Hiroshi Watanabe, CORONA PUBLISHING CO., LTD.

[0013]

[Problem to be Solved by the Invention]

By applying the foregoing CAVLC to the ABT, it can be expected that more efficient entropy coding will also be achieved with the coefficient strings of the ABT.

[0014]

However, the CAVLC achieves the increase of encoding efficiency by optimizing the encoding tables in variable length coding for the respective conditions, based on the maximum number of

coefficients in blocks, and applying the encoding tables to the encoding with switching among them.

[0015]

5 In use of the ABT, the number of coefficients in each block differs depending upon blocks of different sizes; 64 in the case of 8×8 blocks in Fig. 1(b), 32 in the cases of 8×4 and 4×8 blocks in Figs. 1(c) and (d), and 16 in the case of 4×4 blocks in Fig. 1(e). For this reason, the application of the CAVLC requires consideration to the huge number of conditions that can occur in the respective cases.

10 [0016]

For example, supposing the encoding tables are set according to the maximum number of coefficients in coefficient strings, like the encoding tables of runs shown in Fig. 3, the huge number of encoding tables must be prepared; in the case of 8×8 blocks with the number of
15 coefficients being 64, it is necessary to prepare the encoding tables ranging from the encoding table of the number of elements being 2 to the encoding table of the number of elements being 62. Likewise, in the cases of 8×4 and 4×8 blocks with the number of coefficients being 32, the encoding tables must be prepared from that of the number of
20 elements being 2 to that of the number of elements being 30.

[0017]

When the entropy coding adapted to the characteristics of coefficients like the CAVLC was attempted to be applied to the orthogonal transforms selectively using the orthogonal transform
25 blocks of different sizes like the ABT as described above, there was the problem that the number of encoding tables to be prepared became

huge and the memory capacity necessary for retention of the encoding tables became so large. Since it also involved the use of the different encoding tables for blocks of respective sizes and the different selection procedures thereof, there was the problem that the procedure in the entropy coding became complicated and thus implementing means and instrumental structure became complicated.

[0018]

The present invention has been accomplished in order to solve the above problems, and an object of the invention is to provide an image encoding method, an image decoding method, an image encoding apparatus, an image decoding apparatus, an image processing system, an image encoding program, and an image decoding program enabling efficient entropy coding in the orthogonal transform of variable sizes.

[0019]

[Means for Solving the Problem]

In order to achieve the above object, an image encoding method (apparatus) according to the present invention is an image encoding method (apparatus) of dividing image signals into blocks, performing an orthogonal transform of each block, reading resultant orthogonal transform coefficients to obtain a coefficient string, and performing entropy coding thereof, the image encoding method (apparatus) comprising: a block selecting step (means) of selecting a size of a block for the orthogonal transform, out of a plurality of blocks of different sizes; a coefficient string dividing step (means) of, when a block of a size larger than a minimum size is selected in the block selecting step

(means), dividing a coefficient string in the block into a plurality of coefficient strings of a length equal to that of a coefficient string in a block of the minimum size; and an encoding step (means) of performing entropy coding adapted to the coefficient string in the block of the minimum size. An image encoding program according to the present invention is configured to let a computer execute each of the above steps.

[0020]

In the image encoding method according to the present invention, as described above, when a block of a large size is selected to be subjected to the orthogonal transform, the coefficient string in that block is first divided into coefficient strings and then the entropy coding is carried out for each of them. This permits the entropy coding adapted to the coefficient string in the block of the minimum size to be applied to the entropy coding of the coefficient string in the selected block, whereby it is feasible to implement efficient entropy coding of orthogonal transform coefficients, without complicating the procedure of entropy coding.

[0021]

In the above image encoding method (apparatus), the coefficient string dividing step (means) may be configured to read coefficients of the coefficient string from the lowest in a low frequency region and assign the read coefficients one by one in order to the plurality of coefficient strings of the length equal to that of the coefficient string in the block of the minimum size, thereby obtaining the divided coefficient strings. In the above image encoding program,

the coefficient string dividing step executed by the computer may also be configured to read coefficients of the coefficient string from the lowest in a low frequency region and assign the read coefficients one by one in order to the plurality of coefficient strings of the length equal to that of the coefficient string in the block of the minimum size, thereby obtaining the divided coefficient strings.

[0022]

In the above image encoding method (apparatus), the coefficient string dividing step (means) may be configured to read coefficients of the coefficient string from the lowest in a low frequency region and repeatedly perform reading of coefficients by the number equal to the number of coefficients in the coefficient string in the block of the minimum size to obtain a divided coefficient string, thereby obtaining the divided coefficient strings. In the above image encoding program, the coefficient string dividing step executed by the computer may also be configured to read coefficients of the coefficient string from the lowest in a low frequency region and repeatedly perform reading of coefficients by the number equal to the number of coefficients in the coefficient string in the block of the minimum size to obtain a divided coefficient string, thereby obtaining the divided coefficient strings.

[0023]

An image decoding method (apparatus) according to the present invention is an image decoding method (apparatus) of decoding encoded data encoded by an image encoding method of dividing image signals into blocks, performing an orthogonal transform of each block,

reading resultant orthogonal transform coefficients to obtain a coefficient string, and performing entropy coding thereof, the image decoding method (apparatus) comprising: a block selecting step (means) of selecting a size of a block for the orthogonal transform, out of a plurality of blocks of different sizes; a decoding step (means) for performing decoding of the encoded data by entropy coding adapted to a coefficient string in a block of a minimum size out of the plurality of blocks; and a coefficient string constructing step (means) of, when a block of a size larger than the minimum size is selected in the block selecting step (means), constructing a coefficient string of the block of the larger size from a plurality of coefficient strings decoded in the decoding step (means). An image decoding program according to the present invention is configured to let a computer execute each of the above steps.

[0024]

In the image decoding method according to the present invention, as described above, when a block of a larger size is selected to implement decoding of the encoded data subjected to the orthogonal transform, the coefficient string in that block is constructed from coefficient strings of blocks included in that block. This permits a coefficient string to be decoded from the encoded data by the entropy coding adapted to the coefficient string in the block of the minimum size, whereby it is feasible to implement efficient entropy coding of orthogonal transform coefficients, without complicating the procedure of decoding of entropy coding.

[0025]

In the above image decoding method (apparatus), the coefficient string constructing step (means) may be configured to read coefficients in the plurality of coefficient strings decoded in the decoding step (means), from the lowest in a low frequency region and write the coefficients read out of the respective coefficient strings, one by one in order into a new coefficient string from the low frequency region, thereby obtaining the constructed coefficient string. In the above decoding program, the coefficient string constructing step executed by the computer may also be configured to read coefficients in the plurality of coefficient strings decoded in the decoding step, from the lowest in a low frequency region and write the coefficients read out of the respective coefficient strings, one by one in order into a new coefficient string from the low frequency region, thereby obtaining the constructed coefficient string.

[0026]

In the above image decoding method (apparatus), the coefficient string constructing step (means) may be configured to read coefficients in the plurality of coefficient strings decoded in the decoding step (means), from the lowest in a low frequency region and write the read coefficients in units of the original coefficient strings into a new coefficient string from the low frequency region, thereby obtaining the constructed coefficient string. In the above image decoding program, the coefficient string constructing step executed by the computer may also be configured to read coefficients in the plurality of coefficient strings decoded in the decoding step, from the lowest in a low frequency region and write the read coefficients in units

of the original coefficient strings into a new coefficient string from the low frequency region, thereby obtaining the constructed coefficient string.

[0027]

5 An image processing system according to the present invention comprises the above image encoding apparatus and the above image decoding apparatus.

[0028]

10 The image processing system enables efficient entropy coding in the orthogonal transform of variable sizes because of the provision of the above image encoding apparatus and also enables decoding of codes entropy-encoded by the above image encoding apparatus, because of the provision of the above image decoding apparatus.

[0029]

15 [Embodiments of the Invention]

20 The preferred embodiments of the image encoding method, image decoding method, image encoding apparatus, image decoding apparatus, and image processing system according to the present invention will be described below in detail with reference to the drawings. The same elements will be denoted by the same reference symbols throughout the description of the drawings, without redundant description thereof.

[0030]

25 The description will be based on the premise that the encoding and decoding in the description hereinafter are implemented on the basis of H.26L, and the part without specific description about the

operation in the image encoding is supposed to conform to the operation in H.26L. It is, however, noted that the present invention is not limited to H.26L.

[0031]

5 An embodiment of the present invention will be described. In the encoding according to the present embodiment, concerning the orthogonal transform coefficients in blocks of the respective sizes in the ABT of H.26L, a coefficient string obtained from each block is divided into a plurality of coefficient strings each consisting of
10 coefficients in the number equal to the number of coefficients in a coefficient string of a 4×4 block. This makes it feasible to perform the entropy coding by the CAVLC of H.26L defined so as to be adapted to the 4×4 blocks.

[0032]

15 It is assumed that in the encoding, first, the ABT in H.26L is applied to one macroblock, a size achieving the best encoding efficiency is selected out of the blocks shown in Figs. 1(b)-(e), and the orthogonal transform is effected in units of the blocks of the selected size.

20 [0033]

 It is also assumed that the CAVLC in H.26L is employed as the entropy coding of orthogonal transform coefficients. Namely, it is assumed that only the variable length encoding adapted to the encoding of orthogonal transform coefficients for the 4×4 block shown in Fig.
25 1(e) is defined.

[0034]

For example, let us suppose herein that the 8×8 block in Fig. 1(b) is selected. The following readout operation of reading the orthogonal transform coefficients is carried out for this 8×8 block. First, sixty four coefficients in the 8×8 block are read out by zig-zag scan as shown in Fig. 4(a), to obtain a coefficient string as shown in Fig. 4(b).

[0035]

Then this coefficient string is divided into four coefficient strings each consisting of sixteen coefficients, the number of which is the same as the number of coefficients in the coefficient string of the 4×4 block. Here the coefficients in the original coefficient string are read out from the lowest in the low frequency region and alternately assigned to the four coefficient strings, thereby obtaining the coefficient strings after division. Figs. 4(c) and (d) show this readout operation. Since the coefficients are alternately assigned to the respective coefficient strings from the lowest in the low frequency region, the first divided coefficient string is assigned the coefficients read out in the order of the zeroth, fourth, eighth, twelfth,... in the original coefficient string, and the second divided coefficient string is assigned the coefficients read out in the order of the first, fifth, ninth, thirteenth,... in the original coefficient string. The third and fourth divided coefficient strings are not illustrated in Fig. 4.

[0036]

Similarly, when the 8×4 block or 4×8 block of Fig. 1(c) or (d) is selected, thirty two coefficients are divided into two coefficient strings each consisting of sixteen coefficients. The readout method for

obtaining the divided coefficient strings is also similar to that in the case of the 8×8 block except that the number of coefficient strings alternately assigned the coefficients is 2, instead of 4; the coefficients in the original coefficient string are read out from the lowest in the low frequency region and alternately assigned to the two coefficient strings.

[0037]

The coefficient strings obtained in this way are entropy encoded according to the same procedure as the encoding of CAVLC without the use of the ABT, and the encoded data is outputted in order as encoded data of orthogonal transform coefficients in the ABT block.

[0038]

At this time, the CAVLC of H.26L utilizes the space context to switch the applied encoding table on the basis of the number of nonzero coefficients in an adjacent 4×4 block. For this reason, arrangements of coefficient strings after division in the ABT blocks are defined for the ABT blocks larger than the 4×4 block. The definitions are presented in Fig. 5. For example, the 8×8 block shown in Fig. 5(a) is handled on the assumption that the first divided coefficient string illustrated in Fig. 4(c) is located at the position of "1" and the second divided coefficient string illustrated in Fig. 4(d) at the position of "2." It is assumed that, using the definitions of the arrangement, the space context for the divided coefficient strings in the ABT blocks, or the space context for 4×4 blocks adjacent to the ABT blocks is handled in the same manner without any change as in the technique in the CAVLC of H.26L.

[0039]

In the decoding, the original orthogonal transform matrix can be obtained according to the procedure reverse to the procedure in the encoding.

[0040]

5 Let us suppose that the ABT in H.26L is applied to one macroblock, a size is designated out of the blocks shown in Figs. 1(b) to (e), and encoded data from this macroblock is one resulting from the orthogonal transform carried out in units of ABT blocks of the size.

[0041]

10 At this time the encoded data contains encoded data obtained by entropy coding of the divided coefficient strings by the CAVLC, in order as encoded data of orthogonal transform coefficients in the ABT blocks. Accordingly, it is sequentially decoded according to the procedure of CAVLC to obtain the coefficient strings after the division.

15 [0042]

 Since these divided coefficient strings are coefficient strings divided by the readout method shown in Fig. 4, the original orthogonal transform coefficient block can be obtained by conversely writing the coefficients of the divided coefficient strings into each original coefficient string and further writing the resultant coefficient strings into the orthogonal transform coefficient block. The procedure thereafter is the same as the decoding procedure with application of the ABT in H.26L.

20

[0043]

25 A configuration of image processing system 1 for implementing the above image encoding and image decoding will be described below.

Fig. 7 is a block diagram showing image processing system 1 according to an embodiment. The image processing system 1 is composed of image encoding apparatus 10 for encoding image data, and image decoding apparatus 20.

5 [0044]

The image encoding apparatus 10 has orthogonal transform unit 11, coefficient string divider 12, entropy encoder 13, and block selector 14. The orthogonal transform unit 11 has a function of performing the orthogonal transform of image data to transform it into frequency components. The orthogonal transform unit 11 divides each
10 macroblock of the image data into a plurality of blocks and performs the orthogonal transform of the divided blocks. It is connected to block selector 14, and the block selector 14 selects a block capable of implementing the orthogonal transform with the best efficiency.

15 [0045]

The coefficient string divider 12 has a function of dividing a coefficient string obtained by the orthogonal transform, into coefficient strings of a predetermined length. Here the term "predetermined length" is defined as a length of a coefficient string
20 obtained by the orthogonal transform of a block of a minimum size out of the blocks into which a macroblock can be divided for the orthogonal transform of image data by orthogonal transform unit 11.

[0046]

The entropy encoder 13 has a function of encoding the
25 coefficient strings divided by the coefficient string divider 12. Since the coefficient string divider 12 divides the original coefficient string

into the coefficient strings of the same length as that of the coefficient string of the minimum block as described above, the entropy encoder 13 can be configured to be adapted for encoding of the coefficient strings of that length and can perform efficient encoding.

5 [0047]

The image decoding apparatus 20 has entropy decoder 23, coefficient string constructor 22, inverse orthogonal transform unit 21, and block selector 24. The entropy decoder 23 has a function of decoding encoded data.

10 [0048]

The coefficient string constructor 22 has a function of constructing an original coefficient string from coefficient strings divided upon encoding by image encoding apparatus 10. The coefficient string constructor 22 is connected to block selector 24, acquires information about the size of the original block from the block selector 24, and constructs the original coefficient string on the basis of the information. The block selector 24 is able to acquire the size of the original block, based on additional information or the like transmitted with the encoded data from the image encoding apparatus.

20 [0049]

The inverse orthogonal transform unit 21 has a function of transforming the coefficient strings constructed by the coefficient string constructor 22, into image data.

[0050]

25 The image processing system 1 of the structure as described above implements the aforementioned image encoding and image

decoding.

[0051]

In the present embodiment the zig-zag scan was applied to readout of orthogonal transform coefficients, but the readout method of coefficients in application of the present invention does not have to be limited to the zig-zag scan. For example, the present invention may also be applied to cases of application of the field scan for field encoding in interlaced images, which is defined in the ABT of H.26L. In this application, the dividing technique of the coefficient strings in the present embodiment can also be applied as it is.

[0052]

The present embodiment showed the alternate readout method as shown in Fig. 4, as a readout method for obtaining the coefficient strings after the division, but it is also possible to obtain the coefficient strings after the division by another readout method different therefrom. For example, as shown in Figs. 6(c) and (d), sixteen consecutive coefficients each are read out from the original coefficient string from the lowest in the low frequency region and each series is assigned to one of the coefficient strings after the division.

[0053]

In the present embodiment, the readout of orthogonal transform coefficients in the encoding is implemented so as to first perform the first readout for obtaining the coefficient string from the orthogonal transform block and then perform the second readout for obtaining a plurality of coefficient strings after the division. The writing of orthogonal transform coefficients in the decoding is implemented so as

to first perform the first writing for obtaining the coefficient string after construction and then perform the second writing for obtaining the orthogonal transform block. However, the readout and writing of coefficients according to the present invention do not have to be limited to these methods, but may also be implemented by a variety of readout and writing methods that can obtain coefficient strings in the desired arrangement. For example, it is also possible to implement such readout as to immediately obtain a plurality of divided coefficient strings in the first coefficient readout from the orthogonal transform block. The writing from the divided coefficient strings may also be modified so as to immediately obtain the orthogonal transform block in the first coefficient writing.

[0054]

In the present embodiment, the coefficient strings after the division were arranged as shown in Fig. 5, and the space context from the adjacent 4×4 block in the CAVLC in H.26L was assumed to be handled without any change. In this regard, it can also be contemplated that the coefficient strings divided from the coefficient strings of the ABT blocks larger than the 4×4 block are originally different in the property from the coefficient strings in the case of the 4×4 block and weights are given to numerals used as the space context. Specifically, where the number of nonzero coefficients is used as the space context from the adjacent block, a constant is always added to or multiplied by the number of nonzero coefficients in each divided coefficient string obtained from an ABT block larger than the 4×4 block, when used as the space context. In another configuration,

where the coefficient strings after the division are obtained by continuously reading out the coefficients from the lowest in the low frequency region as shown in Fig. 6, different constants may be added to or multiplied by coefficients read out from the low frequency region and coefficients read out from the high frequency region.

[0055]

The embodiments were described on the premise that the encoding and decoding were substantialized on the basis of H.26L and were described based on the ABT and CAVLC in H.26L. However, it is noted that the image encoding methods to which the present invention can be applied are not limited to H.26L, and the present invention can be applied to various image encoding methods permitting selection among a plurality of sizes of blocks for the orthogonal transform and using the entropy coding adapted to the orthogonal transform coefficients.

[0056]

[Effects of the Invention]

The image encoding method, image decoding method, image encoding apparatus, image decoding apparatus, and image processing system according to the present invention provide the following effect, as detailed above. Namely, where a size of a block for the orthogonal transform can be selected from a plurality of sizes, a coefficient string consisting of resultant orthogonal transform coefficients is divided into a plurality of coefficient strings of the same size as that of the coefficient string in the block of the minimum size and each of these coefficient strings is subjected to the entropy coding adapted to the

coefficient string in the block of the minimum size; whereby it is feasible to implement the efficient entropy coding, without increase in the number of encoding tables in the entropy coding and without complicating the encoding tables and the procedure of selection thereof.

[Brief Description of the Drawings]

[Fig. 1]

A figure including diagrams showing the orthogonal transform blocks used in the Adaptive Block size Transforms (ABT) of H.26L.

[Fig. 2]

A figure including diagrams showing a readout method of reading coefficients in a 4×4 block, and an example of a coefficient string after readout.

[Fig. 3]

A diagram showing the encoding tables of runs used in the Context-based Adaptive Variable Length Code (CAVLC) of H.26L.

[Fig. 4]

A figure including diagrams showing an example in which a method of readout and division of orthogonal transform coefficients according to the present invention is carried out for an 8×8 block.

[Fig. 5]

A figure including diagrams showing definitions of arrangement in original blocks, of coefficient strings after division according to the present invention.

[Fig. 6]

A figure including diagrams showing an example in which

another method of readout and division of orthogonal transform coefficients according to the present invention is carried out for an 8×8 block.

[Fig. 7]

5 A block diagram showing a configuration of an image processing system according to an embodiment.

[Explanation of Reference Numerals]

10 1 - image processing system, 10 - image encoding apparatus, 11 - orthogonal transform unit, 12 - coefficient string divider, 13 - entropy encoder, 14 - block selector, 20 - image decoding apparatus, 21 - inverse orthogonal transform unit, 22 - coefficient string constructor, 23 - entropy decoder, 24 - block selector.

[Document Name] Abstract

[Abstract]

[Object] To provide an image encoding apparatus capable of achieving efficient entropy coding in the orthogonal transform of variable sizes.

5 [Means of Solution] Image encoding apparatus 10 according to the present invention is an image encoding apparatus 10 for dividing image signals into blocks, performing an orthogonal transform of each block, reading resultant orthogonal transform coefficients to obtain a coefficient string, and performing entropy coding, which has block
10 selector 14 for selecting a size of a block for the orthogonal transform, out of a plurality of blocks of different sizes; coefficient string divider 12 for, when a block of a size larger than a minimum size is selected by block selector 14, dividing a coefficient string in the block into a plurality of coefficient strings of a length equal to that of a coefficient
15 string in a block of the minimum size; and encoder 13 for performing entropy coding adapted to the coefficient string in the block of the minimum size.

[Selected Drawing] Fig. 7

20

Fig. 1





Fig. 2

~~Fig. 2A~~



(a) READOUT OF
ORTHOGONAL TRANSFORM COEFFICIENTS

~~Fig. 2B~~



(b) COEFFICIENT STRING AFTER READOUT

~~Fig. 2C~~

NO.	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
COEFFICIENT VALUE	16	0	0	8	4	0	1	0	2	1	0	0	1	0	0	0

(c) EXAMPLE OF COEFFICIENT STRING AFTER READOUT


Fig.3

TABLE RUN	1	2	3	4	5	6	>6
0	1	1	11	11	11	11	111
1	0	01	10	10	10	000	110
2	-	00	01	01	011	001	101
3	-	-	00	001	010	011	100
4	-	-	-	000	001	010	011
5	-	-	-	-	000	101	010
6	-	-	-	-	-	100	001
7	-	-	-	-	-	-	0001
8	-	-	-	-	-	-	00001
9	-	-	-	-	-	-	000001
10	-	-	-	-	-	-	0000001
11	-	-	-	-	-	-	00000001
12	-	-	-	-	-	-	000000001
13	-	-	-	-	-	-	0000000001
14	-	-	-	-	-	-	00000000001

Fig. 4


~~Fig. 4A~~

(a) COEFFICIENT MATRIX
BEFORE READOUT




~~Fig. 4B~~

(b) COEFFICIENT STRING
AFTER READOUT



~~Fig. 4C~~

(c) FIRST DIVIDED
COEFFICIENT STRING



~~Fig. 4D~~

(d) SECOND DIVIDED
COEFFICIENT STRING






Fig. 5

~~Fig. 5A~~




(a) DEFINITION OF ARRANGEMENT OF
DIVIDED COEFFICIENT STRINGS IN 8×8 BLOCK

~~Fig. 5B~~



(b) DEFINITION OF ARRANGEMENT OF
DIVIDED COEFFICIENT STRINGS IN 8×4 BLOCK

~~Fig. 5C~~




(c) DEFINITION OF ARRANGEMENT OF
DIVIDED COEFFICIENT STRINGS IN 4×8 BLOCK

Fig. 6

~~Fig. 6A~~

(a) COEFFICIENT MATRIX
BEFORE READOUT




~~Fig. 6B~~

(b) COEFFICIENT STRING
AFTER READOUT



~~Fig. 6C~~

(c) FIRST DIVIDED
COEFFICIENT STRING



~~Fig. 6D~~

(d) SECOND DIVIDED
COEFFICIENT STRING





Fig.7



Tab C